



Simply Better Connections

UC8000

MicLIVE™ 6-CH
AI Audio Mixer
User Manual

Compliance Statements

FEDERAL COMMUNICATIONS COMMISSION INTERFERENCE STATEMENT

This equipment has been tested and found to comply with the limits for a Class B digital service, pursuant to Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. Any changes or modifications made to this equipment may void the user's authority to operate this equipment. This equipment generates, uses, and can radiate radio frequency energy. If not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- ♦ Reorient or relocate the receiving antenna.
- ♦ Increase the separation between the equipment and receiver.
- ♦ Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- ♦ Consult the dealer or an experienced radio/TV technician for help.

The device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.



KCC Statement

유선 제품용 / B 급 기기 (가정용 방송 통신 기기)
이 기기는 가정용 (B 급) 전자파적합기기로서 주로 가정에서 사용하는
것을 목적으로 하며, 모든 지역에서 사용할 수 있습니다.

Industry Canada Statement

This Class B digital apparatus complies with Canadian ICES-003.

CAN ICES-003 (B) / NMB-003 (B)**RoHS**

This product is RoHS compliant.



D33866
RoHS

Product Name: 6-CH AI Audio Mixer, Model: UC8000						
Unit	Restricted Substances and Their Chemical Symbols					
	Lead (Pb)	Mercury (Hg)	Cadmium (Cd)	Hexavalent chromium (Cr ⁺⁶)	Polybromina ted biphenyls (PBB)	Polybromina ted diphenyl ethers (PBDE)
Cable	—	O	O	O	O	O
PCBA	—	O	O	O	O	O
Plastic / Other Parts	O	O	O	O	O	O
Metal Parts	—	O	O	O	O	O

Note:

1. "Exceeding 0.1 wt %" and "exceeding 0.01 wt %" indicate that the percentage content of the restricted substance exceeds the reference percentage value of presence condition.
2. "O" Indicates that the percentage content of the restricted substance does not exceed the percentage of reference value of presence.
3. "—" indicates that the restricted substance corresponds to the exemption.

User Information

Online Registration

Be sure to register your product at our online support center:

International	http://eservice.aten.com
---------------	---

Telephone Support

For telephone support, call this number:

International	886-2-8692-6959
China	86-400-810-0-810
Japan	81-3-5615-5811
Korea	82-2-467-6789
North America	1-888-999-ATEN ext 4988 1-949-428-1111

User Notice

All information, documentation, and specifications contained in this manual are subject to change without prior notification by the manufacturer. The manufacturer makes no representations or warranties, either expressed or implied, with respect to the contents hereof and specifically disclaims any warranties as to merchantability or fitness for any particular purpose. Any of the manufacturer's software described in this manual is sold or licensed *as is*. Should the programs prove defective following their purchase, the buyer (and not the manufacturer, its distributor, or its dealer), assumes the entire cost of all necessary servicing, repair and any incidental or consequential damages resulting from any defect in the software.

The manufacturer of this system is not responsible for any radio and/or TV interference caused by unauthorized modifications to this device. It is the responsibility of the user to correct such interference.

The manufacturer is not responsible for any damage incurred in the operation of this system if the correct operational voltage setting was not selected prior to operation. PLEASE VERIFY THAT THE VOLTAGE SETTING IS CORRECT BEFORE USE.

Product Information

For information about all ATEN products and how they can help you connect without limits, visit ATEN on the Web or contact an ATEN Authorized Reseller. Visit ATEN on the Web for a list of locations and telephone numbers:

International	http://www.aten.com
North America	http://www.aten-usa.com

Package Contents

Check to make sure that all components are in working order. If you encounter any problem, please contact your dealer.

- 1 MicLIVE™ 6-CH MicLIVE™ 6-CH AI Audio Mixer
- 1 USB Type-C cable
- 1 user instructions

Contents

Compliance Statements	ii
User Information	iii
Online Registration	iv
Telephone Support	iv
User Notice	iv
Product Information	v
Package Contents	v
Table of Contents	vi
About this Manual	viii
Conventions	ix

4. Introduction

Overview	1
MicLIVE™ 6-CH	1
OnAir™ Audio	1
No Prior Knowledge Needed	2
Features	2
MicLIVE™ 6-CH Components	3
Top	3
Rear / Side	4
OnAir™ Audio GUI	5

5. Getting Started

Audio Mixing Flowchart	7
1. Items to Prepare	8
2. Connecting Your Audio Devices	9
3. Installing OnAir™ Audio on Your Host Computer	11
4. Tuning Your Audio Devices	12
Tuning Each Audio Track Independently	12
Tuning Your Audio Mix	13

6. AI Smart EQ

Try It! (Using AI Smart EQ)	16
---------------------------------------	----

7. Auto Ducking

Try It! (Applying Auto Ducking)	17
Adjusting Auto Ducking	18
Auto Ducking for Input 3 Only (Input 4 Disabled)	18
Auto Ducking for Input 4 Only (Input 3 Disabled)	18

8. Jingles (Audio Effects)

Try It! (Using Jingles)	19
How to Customize Your Jingles	20
Recording a Jingle	20
Downloading a Recorded Jingle	21
Replacing a Jingle with an Audio File	22
Adjusting a Jingle	23

9. Voice FX

Try It! (Applying Voice FX)	26
Applying Voice FX via MicLIVE™ 6-CH	26
Applying Voice FX via OnAir™ Audio	28
How to Define a Customized Voice FX	29
Using Custom Voice FX	31

10. Advanced Audio Settings

Configuring Audio Inputs	33
--------------------------------	----

11. Other Settings (including Updates)

Settings Page	35
Updating Firmware / Application	36
Resetting to Factory Default	36

Appendix

Safety Instructions	37
General	37
Technical Support	39
International	39
North America	39
Specifications	40
Limited Warranty	41

About this Manual

This manual is provided to help you get the most out of your MicLIVE™ 6-CH. It covers all aspects of the device, including installation, configuration, and operation.

Items covered in this manual include:

Model	Product Name
UC8000	MicLIVE™ 6-CH AI Audio Mixer (hardware)
OnAir™ Audio	OnAir™ Audio Mixer (software)

An overview of the information covered is provided below.

Chapter 1, Introduction introduces you to MicLIVE™ 6-CH AI Audio Mixer and its coupled application OnAir™ Audio, with their purpose, features, and components described.

Chapter 2, Getting Started provides an audio mixing flowchart that covers all of the steps that are involved in producing your audio mix.

Chapter 3, AI Smart EQ explains the AI Smart EQ functions and how to use it.

Chapter 4, Auto Ducking explains the ducking functions and how to use it.

Chapter 5, Jingles (Audio Effects) describes the 8 jingles (effects) pads provided by MicLIVE™ 6-CH.

Chapter 6, Voice FX describes the Voice FX (voice changer) modes provided by the MicLIVE™ 6-CH, and how to define a customized Voice FX.

Chapter 7, Advanced Audio Settings describes the various advanced audio settings that can be adjusted via OnAir™ Audio.

Chapter 8, Other Settings (including Updates) describes other settings provided by OnAir™ Audio, including how to update the firmware and application, as well as how to reset the mixer back to factory default settings.

Appendix provides a list of safety instructions and precautions, product specifications, and other technical information.

Note:

- ♦ Read this manual thoroughly and follow the installation and operation procedures carefully to prevent any damage to the unit or connected devices.
 - ♦ ATEN regularly updates its product documentation for new features and fixes. For an up-to-date MicLIVE™ 6-CH documentation, visit <http://www.aten.com/global/en/>
-

Conventions

This manual uses the following conventions:

Monospaced	Indicates text that you should key in.
[]	Indicates keys you should press. For example, [Enter] means to press the Enter key. If keys need to be chorded, they appear together in the same bracket with a plus sign between them: [Ctrl+Alt].
1.	Numbered lists represent procedures with sequential steps.
♦	Bullet lists provide information, but do not involve sequential steps.
>	Indicates selecting consecutive options (such as on a menu or dialog box). For example, Start > Run means to open the <i>Start</i> menu, and then select <i>Run</i> .
	Indicates critical information.

This Page Intentionally Left Blank

Chapter 1

Introduction

Overview

MicLIVE™ 6-CH

MicLIVE™ 6-CH is a compact, bus-powered, 6-channel AI audio mixer that can connect up to 6 audio devices (4 sources and 2 headphones) and instantly transform them into a live podcast or digital music event from anywhere.

Featuring AI Smart EQ, the MicLIVE™ 6-CH AI Audio Mixer can automatically detect for and calibrate its equalizer according to your voice and recording environment, using a microphone, for an optimal voice recording performance.

Presented with 3 audio in ports, 2 x XLR combo and 1 x 3.5-mm TRRS, and 1 bidirectional USB-C port, the mixer can connect with 2 main audio instruments (via the XLR combo ports), such as microphones and guitars, 1 sub audio device (via the 3.5-mm TRRS), such as for background music, and 1 host computer (via the USB-C) for recording the audio mix produced while functioning as a second sub audio source when needed. In addition, the mixer also provides 2 headphone jacks (3.5-mm TRS) for real-time monitoring of its audio inputs and audio mix.

For added versatility, MicLIVE™ 6-CH is compatible with +48V microphones and offers automated ducking of sub audio, as well as 4 Voice FX (voice changer) modes and 8 customizable jingles that you can use freely.

OnAir™ Audio

Coupled with OnAir™ Audio, an intuitive software dedicated to MicLIVE™ 6-CH, users can easily view and adjust the volume, status, and settings of each of the audio device connected, as well as the audio mix produced using a Windows computer.

No Prior Knowledge Needed


Together, MicLIVE™ 6-CH with OnAir™ Audio, boasts as the best way to start your first podcast instantly and effortlessly, novice or expert! To get started, simply connect your microphone and host computer, installed with OnAir™ Audio, and you are ready to go.

Features

- ♦ All-in-one design to simplify audio mixing and podcast workflow — offers up to 6-channel audio inputs, DSP and AD / DA converter
- ♦ High-res audio up to 24 bit / 96 kHz via USB-C onto a PC or Mac
- ♦ The world's first AI-powered audio mixer — enhances microphone audio quality with AI sound check so anyone can have a high-quality recording
- ♦ Jingle pad saves up to 8 sound effects that can be customized from audio sources from a computer, microphone, and any other audio inputs for professional audio mixing
- ♦ The auto ducking function lowers background music anytime one speaks, ensuring the speaker's voice is always heard, loud and clear, during broadcasting

MicLIVE™ 6-CH Components


Top




Rear / Side

Output / Input 4: connects to host computer via USB-C
(for bus power, audio mix output, and input 4)

Input 3: connects to sub audio (BGM)
via 3.5 mm TRRS




: connects up to 2 main audio (mic / musical instrument)
via XLR combo



: connects up to 2 headphones
via 3.5 mm TRS
(for monitoring audio mix)

OnAir™ Audio GUI (Graphical User Interface)

Below provides a quick look at the OnAir™ Audio software that shall be installed on the host computer that connects to your MicLIVE™ 6-CH.



Note: For details on connecting MicLIVE™ 6-CH and installing OnAir™ Audio, respectively see *2. Connecting Your Audio Devices*, page 9, and *3. Installing OnAir™ Audio on Your Host Computer*, page 11.

This Page Intentionally Left Blank

Chapter 2

Getting Started



Please review the safety information regarding the placement of the mixer before starting (see *Safety Instructions*, page 37).

Audio Mixing Flowchart

Refer to the flowchart below that will guide you through how to use the MicLIVE™ 6-CH AI Audio Mixer from start to finish.

■ Preparation

1. What to prepare?
see 1. *Items to Prepare*, page 8
2. How to connect?
see 2. *Connecting Your Audio Devices*, page 9
3. How to install OnAir™ Audio on your host computer?
see 3. *Installing OnAir™ Audio on Your Host Computer*, page 11

■ Testing Audio

4. How to tune each audio track (input) and the audio mix as a whole?
see 4. *Tuning Your Audio Devices*, page 12

■ Audio Mixing

5. What is *AI Smart EQ* and how to use it?
see *AI Smart EQ*, page 15
6. What is *Auto Ducking* and how to use it?
see *Auto Ducking*, page 17

■ Advanced Functions

7. What are *jingles (audio effects)* and how to use them?
see *Jingles (Audio Effects)*, page 19

8. What is *Voice FX* and how to use it?
see *Voice FX*, page 25

1. Items to Prepare

Below is a list of items you should prepare before using your MicLIVE™ 6-CH AI Audio Mixer.

- ♦ 1 host computer (for power and *OnAir™ Audio*) with the following specs:

OnAir™ Audio system requirements	
OS	Windows 10 (64-bit)
Processor	Intel multi-core i3/5/7 series 2 GHz (or AMD equivalent) or above
Memory	Minimum: 2 GB RAM Recommended: 8 GB RAM
Storage	100 MB available hard disk space
USB	USB-C compatible

- ♦ 1 ~ 2 main audio devices as exemplified below.


Examples of main audio devices	
microphone	♦ dynamic or condenser (up to +48V) ♦ XLR or 6.35 mm TRS compatible
musical instrument	XLR or 6.35 mm TRS compatible

- ♦ 1 ~ 2 headphones (3.5 mm TRS compatible)
- ♦ 1 sub audio device (3.5 mm TRRS compatible; for background music)


2. Connecting Your Audio Devices

To connect your audio devices, do the following.

1. Connect your host computer, installed with OnAir™ Audio (see 3. *Installing OnAir™ Audio on Your Host Computer*, page 11, for details), to the mixer with the USB-C cable provided




2. Connect 1 ~ 2 main audio devices, such as microphones and/or musical instruments, to the mixer using self-supplied XLR and/or 6.35 mm TRS cables.




Note: If your microphone doesn't work, try applying +48V. See 4. *Tuning Your Audio Devices*, page 12, for details, specifically Step 2 ~ 5.

3. Connect 1 ~ 2 headphones to the mixer for listening to your audio mix via its 3.5 mm TRS headphone ports



4. (Optional) Using a self-supplied 3.5 mm TRRS cable, connect 1 sub audio device, such as a mobile device, to the mixer's *input 3* for bidirectional audio, e.g. implementing background music while conducting a remote interview.




Once connected, you can test and tune each audio device by listening through the headphones (see 4. *Tuning Your Audio Devices*, page 12).

3. Installing OnAir™ Audio on Your Host Computer

To install OnAir™ Audio, an audio mixing software exclusively designed for MicLIVE™ 6-CH AI Audio Mixer, do the following.

1. On your host computer, which is used to connect to and power your MicLIVE™ 6-CH, go to the audio mixer's download page by accessing <https://tinyurl.com/nsp6tnfn>.
2. From the download page, download and install OnAir™ Audio.
3. Once installed, launch ATEN OnAir™ Audio. The following graphical user interface (GUI) appears.



4. Tuning Your Audio Devices

Tuning Each Audio Track Independently

To test and tune a main / sub audio, do the following.

1. First, mute all incoming audio except for the one you are tuning using 1 of the 2 following methods.


- ♦ **on MicLIVE™ 6-CH Mixer:** to mute an audio, select that audio by pressing , , or  (press once or twice for input 3 or 4).

Then press .

- ♦ **via OnAir™ Audio:** to mute an audio, click **Mute** below that audio.



2. Second, make sure your headphones are properly connected and have an adequate output volume by adjusting the mixer's




3. Select the main / sub audio you want to test and tune by pressing , , or  (press once or twice for input 3 or 4) on the mixer.


4. Then select the input modes you want to set it as:

- ♦ **Ins. (Instrumental)** : applies EQ settings that are ideal for musical instruments.
- ♦ **+48 V** : applies +48 V to microphones that require so.

- ♦ **AI (AI Smart EQ)** : must be calibrated before use (see *AI Smart EQ*, page 15, for details), applies AI Smart EQ that automatically adjusts the mixer's equalizer according to your voice and recording environment.
5. Adjust the volume of the main / sub audio as desired.
- ♦ **via MicLIVE™ 6-CH:** adjust by using




- ♦ **via OnAir™ Audio:** adjust by using the volume T-bar




Tuning Your Audio Mix

6. Once every audio track has been tuned, unmute each audio track you want to use in forming your audio mix, using 1 of the 2 following methods.
- ♦ **on MicLIVE™ 6-CH Mixer:** to unmute an audio, select an audio that's muted by pressing , , or  (press once or twice for input 3 or 4). Then press  to disable mute.
 - ♦ **via OnAir™ Audio:** to unmute an audio, disable mute by clicking **Mute** below an audio that's muted.



7. After all audio tracks you want to use are unmuted, adjust the volume of each as needed.
- ♦ **on MicLIVE™ 6-CH Mixer:** to adjust the volume of an audio, select by pressing , , or  (press once or twice for input 3 or 4). Then adjust by using



- ♦ **via OnAir™ Audio:** to adjust the volume of an audio, use the volume T-bar below it.



Note: Your host computer, installed with OnAir™ Audio, must be connected to the mixer for the software to work.

Chapter 3

AI Smart EQ

AI Smart EQ is MicLIVE™ 6-CH's signature function that can automatically adjust the mixer's equalizer settings according to your voice audio and recording environment for an optimal voice recording performance.




Note: AI Smart EQ is only recommended to be used for voice recording.

Try It! (Using AI Smart EQ)

Prior to using AI Smart EQ, it must first be calibrated in an environment that's the same or similar to your voice recording scenario.

1. Select the audio input you want AI Smart EQ to be calibrated for and applied to by pressing  or  on the mixer.
2. To start calibrating, do one of the following.
 - ♦ If this is your first time using AI Smart EQ, you can start calibrating it by pressing **AI (AI Smart EQ)**  once.
 - ♦ If this is not your first time using AI Smart EQ, you can recalibrate it by long pressing **AI (AI Smart EQ)**  (about 3 seconds) until the mixer's *Effects* button start to flash.
3. When the mixer's *Effects* buttons start to flash in sequence, as exemplified below, start speaking through the microphone mimicking your voice recording scenario until the buttons no longer flash. This shall take about 10 ~ 15 seconds.



Once AI Smart EQ has been calibrated, it is automatically applied to the audio track currently selected.

Chapter 4


Auto Ducking

MicLIVE™ 6-CH's *Auto Ducking* function, when applied, can automatically lower the volumes of the mixer's sub audio (input 3 & input 4) whenever there's sound detected coming from the mixer's main audio (microphone 1 and/or 2).

This function is especially useful during a music podcast, where the host does not need to manually lower the volume of music played through input 3 and/or 4 when speaking.

Try It! (Applying Auto Ducking)

1. To apply auto ducking, simply press  on your MicLIVE™ 6-CH AI Audio Mixer.



2. Once applied, while playing music through the mixer's input 3 and/or 4, try speaking through a connected microphone. The volumes of inputs 3 & 4 shall be lowered automatically when you speak.

Adjusting Auto Ducking

By default, auto ducking is applied to both inputs 3 and 4. If you want auto ducking to be applied only to input 3 or input 4, but not the other, do the following.

1. Make sure auto ducking is applied by pressing  so that its LED is lit.
2. Select input 3 or 4 by pressing  once (green) or twice (blue).
3. Once you have selected input 3 or 4, the  button's LED shall be either flashing or lit, as explained below.

Ducking Status	Description
 flashing	Auto ducking is enabled for the input selected (input 3 or 4).
 lit and not flashing	Auto ducking is disabled for the input selected (input 3 or 4)

4. You can change the status of the  by long pressing it for 3 seconds, i.e. enabling / disabling auto ducking for input 3 or 4.

Note: Auto ducking cannot be disabled for both inputs 3 and 4 at the same time. Disabling input 3 or 4 will automatically enable the other.

Auto Ducking for Input 3 Only (Input 4 Disabled)

When auto ducking is applied only to input 3, input 3's volume is lowered automatically whenever there's sound detected coming from any of the mixer's other audio inputs (microphone 1 & 2 and input 4).

Auto Ducking for Input 4 Only (Input 3 Disabled)

When auto ducking is applied only to input 4, input 4's volume is lowered automatically whenever there's sound detected coming from any of the mixer's other audio inputs (microphone 1 & 2 and input 4).

Chapter 5

Jingles (Audio Effects)

To add a personalized touch to your podcast show and/or digital music event, MicLIVE™ 6-CH provides 8 customizable jingle (audio effect) pads for you to play the wanted sound effects whenever you see fit, e.g. crowd laughter sounds right after a joke, a round of applause after introducing a guest, etc.



Jingle (audio effect) pads
on MicLIVE™ 6-CH



Jingle (audio effect) buttons
on ATEN OnAir™ Audio

Try It! (Using Jingles)

- ♦ **on MicLIVE™ 6-CH Mixer:** simply press any 1 of the 8 jingle pads on your mixer.
- ♦ **via OnAir™ Audio:** to play a jingle, simply click any 1 of the 8 jingle icons on the ATEN OnAir Audio software on your connected host computer.

How to Customize Your Jingles


There are two ways to customize a jingle, as described below:

- ♦ Record a jingle using the audio devices connected to your MicLIVE™ 6-CH AI Audio Mixer (see *Recording a Jingle*, below).
- ♦ Uploading a jingle via OnAir™ Audio on your connected host computer (see *Replacing a Jingle with an Audio File*, page 22).

Recording a Jingle

You can replace any existing jingle using sounds recorded through your connected audio devices. The maximum length of a jingle is 20 seconds.

1. To record a jingle, long press (about 3 seconds) the jingle pad you want to replace until it starts flashing, indicating that it is ready to record.




Note: If you change your mind and want to cancel, long press (about 3 seconds) the flashing jingle pad again to exit record mode.

2. To start recording, press the flashing jingle pad, and then press it again to stop recording once you are done.


Downloading a Recorded Jingle

If you want to download the jingle you've recorded onto your host computer, you can do so by doing the following.


1. On your connected host computer, click  in OnAir™ Audio's jingles section.



2. On the jingle settings page that appears, select the jingle you want to download.



3. Click **Download** to save the jingle onto your connected host computer as an audio file.




Replacing a Jingle with an Audio File

You can replace any existing jingle with an *.wav audio file from your connected host computer via OnAir™ Audio.


1. To replace a jingle with an audio file, click  in OnAir™ Audio's jingles section.




2. On the jingle settings page that appears, select the jingle you want to replace.



3. Click **Replace** to browse for and select the audio file you want to replace the jingle with (only the first 20 seconds is used if it is longer than 20 s).




4. Click **Apply** to save your settings.




Adjusting a Jingle

To adjust jingles, via OnAir™ Audio on your connected host computer, access the jingle settings page by clicking  on the upper-right corner of the software's jingles section.



The following settings appear.



Component	Description
Icon	Selects an icon to represent the jingle.
Playback	Selects method in which the jingle is played back. ♦ Play / Stop: Plays the jingle from start to finish. ♦ Loop / Stop: Repeats the jingle endlessly until clicking again to stop. ♦ Play / Overlap: Plays the jingle and click again to replay from start.
Color	Selects a color for the jingle.

This Page Intentionally Left Blank

Chapter 6

Voice FX

By default, MicLIVE™ 6-CH offers 4 Voice FX (voice changer) modes that can be applied during voice recording via the microphones connected.

The 4 Voice FX modes include:

Voice FX	Color	Description
Pitch		Elevates the pitch of your voice.
Reverb		Fills up your voice for a more “full” and “natural” effect.
Male		Changes a female voice to male.
Female		Changes a male voice to female.

Note: By default, Voice FX only affects microphones connected via *Mic 2* but not *Mic 1*. If you want Voice FX to be applied to microphones connected via *Mic 1*, click  next to *Mic 1* on the OnAir™ Audio on your connected host computer, and then enable **Voice FX**, as illustrated below.



For further details on adjusting audio input settings, see *Configuring Audio Inputs*, page 33.


Try It! (Applying Voice FX)

There are two ways of applying Voice FX.

- ♦ to apply Voice FX on your **MicLIVE™ 6-CH Mixer**, see *Applying Voice FX via MicLIVE™ 6-CH*, page 26.
- ♦ to apply Voice FX via **OnAir™ Audio** on your host computer, see *Applying Voice FX via OnAir™ Audio*, page 28.

Applying Voice FX via MicLIVE™ 6-CH

1. To apply Voice FX your MicLIVE™ 6-CH, simply press **MODE**, 1 ~ 4 times, on the mixer.



- ♦ *Pitch*: press **MODE** once, where it shall be lit in **white**.
- ♦ *Reverb*: press **MODE** twice, where it shall be lit in **red**.
- ♦ *Male*: press **MODE** 3 times, where it shall be lit in **green**.
- ♦ *Female*: press **MODE** 4 times, where it shall be lit in **blue**.

2. If you want to adjust the strength of the Voice FX mode applied, simply rotate the mixer's Voice FX strength controller.



- ◆ Rotate clockwise to increase the strength of Voice FX applied.
- ◆ Rotate counterclockwise to decrease the strength of Voice FX applied.

Note: If you want to define a customized Voice FX mode, see *How to Define a Customized Voice FX*, page 29.

Applying Voice FX via OnAir™ Audio

- 1. To apply Voice FX via OnAir™ Audio on your connected host computer, simply click 1of the 4 **Voice FX icons** on the software.




Note: *Custom* is only available after you have defined a customized Voice FX mode of your own. See *How to Define a Customized Voice FX*, page 29.

- 2. After selecting a Voice FX mode, adjust its strength by clicking , and clicking and dragging its **strength T-bar**, as exemplified below.




How to Define a Customized Voice FX


1. To define *Custom Voice FX*, access OnAir™ Audio's **Settings** tab on your connected host computer. Then select **Voice FX**



2. Enable **CUSTOM**.




3. Once enabled, the following settings are enabled.




4. Select a color, in which the mixer's *Mode* button will be lit, for *Custom Voice FX* from the color dropdown menu




5. Select **Preset 1**. Once selected, this is the *Preset* that your customized Voice FX settings will be saved under.



6. Enable **EQ** and define a set of Voice FX settings you want to save under the *Preset*, as exemplified below.



7. Click **Apply** to save your settings.




8. If you want to define more than 1 set of customized Voice FX settings, select another *Preset*, e.g. **Preset 2**, and repeat Step 5 ~ 7.

Note: OnAir™ Audio can define and save up to 6 sets of customized Voice FX settings, under **Preset 1 ~ Preset 6**.

Using Custom Voice FX

After defining the *Custom Voice FX*, you can apply it by doing the following.

1. Press press **MODE** 5 times on your MicLIVE™ 6-CH Mixer, where it shall be lit in the color that *Custom Voice FX* is set as.
2. Rotate the mixer's Voice FX strength controller to select the *Preset* you want to use.



This Page Intentionally Left Blank

Chapter 7

Advanced Audio Settings


Through OnAir™ Audio, you can adjust the advanced audio settings for each of your main / sub audio.

Configuring Audio Inputs

To access the advanced audio settings of a main / sub audio, click  next to that audio on the OnAir™ Audio on your connected host computer, as exemplified below.



The following settings appear.



Component	Description
Voice FX	Enables / disables Voice FX for the audio input, as explained below. ◆ Enabled: When <i>Voice FX</i> mode is applied, it is applied to this audio. ◆ Disabled: When <i>Voice FX</i> mode is applied, it is not applied to this audio.
Compressor	Enables / disables Compressor for the audio input, and provides compressor-related settings.
AI Smart EQ	Selects the frequency level, Low , Medium , or High , <i>AI Smart EQ</i> is most sensitive to when it is being calibrated.


Chapter 8

Other Settings (including Updates)

This chapter covers other settings provided by OnAir™ Audio, including firmware / application update, reset to factory default settings, and tutorial.

Settings Page


To access OnAir™ Audio's *Settings* page, select **Settings > Others**. The following page appears.




Component	Description
Tutorial	Provides tips on how to use MicLIVE™ 6-CH AI Audio Mixer, including: ◆ How to connect audio devices. ◆ How to use the following functions: ◆ AI Smart EQ ◆ Jingles (Effects) ◆ Voice FX ◆ Ducking
Firmware / Application	Displays the current version of firmware / application and lets you update it to the latest version.
Factory Reset	Resets the mixer to factory default settings.

Updating Firmware / Application

1. To update your MicLIVE™ 6-CH Mixer's firmware or the OnAir™ Audio application, select **Settings > Others** on OnAir™ Audio.




2. Click **Update** next to the item you want to update, *Firmware* or *Application*.




3. If you're asked to browse for an update file, download it from the mixer's download page at <https://tinyurl.com/nsp6tnfn>.

Resetting to Factory Default

1. To reset your MicLIVE™ 6-CH Mixer back to factory default settings, select **Settings > Others** on OnAir™ Audio.



2. Click **Reset** next to *Factory Reset*.



Safety Instructions

General

- ♦ This product is for indoor use only.
- ♦ Read all of these instructions. Save them for future reference.
- ♦ Follow all warnings and instructions marked on the device.
- ♦ Do not place the device on any unstable surface (cart, stand, table, etc.). If the device falls, serious damage will result.
- ♦ Do not use the device near water.
- ♦ Do not place the device near, or over, radiators or heat registers.
- ♦ The device cabinet is provided with slots and openings to allow for adequate ventilation. To ensure reliable operation, and to protect against overheating, these openings must never be blocked or covered.
- ♦ The device should never be placed on a soft surface (bed, sofa, rug, etc.) as this will block its ventilation openings. Likewise, the device should not be placed in a built in enclosure unless adequate ventilation has been provided.
- ♦ Never spill liquid of any kind on the device.
- ♦ Unplug the device from the wall outlet before cleaning. Do not use liquid or aerosol cleaners. Use a damp cloth for cleaning.
- ♦ The device should be operated from the type of power source indicated on the marking label. If you are not sure of the type of power available, consult your dealer or local power company.
- ♦ To prevent damage to your installation it is important that all devices are properly grounded.
- ♦ Do not allow anything to rest on the power cord or cables. Route the power cord and cables so that they cannot be stepped on or tripped over.
- ♦ Position system cables and power cables carefully; Be sure that nothing rests on any cables.
- ♦ Never push objects of any kind into or through cabinet slots. They may touch dangerous voltage points or short out parts resulting in a risk of fire or electrical shock.
- ♦ Do not attempt to service the device yourself. Refer all servicing to qualified service personnel.

- ♦ If the following conditions occur, unplug the device from the wall outlet and bring it to qualified service personnel for repair.
 - ♦ The power cord or plug has become damaged or frayed.
 - ♦ Liquid has been spilled into the device.
 - ♦ The device has been exposed to rain or water.
 - ♦ The device has been dropped, or the cabinet has been damaged.
 - ♦ The device exhibits a distinct change in performance, indicating a need for service.
 - ♦ The device does not operate normally when the operating instructions are followed.
- ♦ Only adjust those controls that are covered in the operating instructions. Improper adjustment of other controls may result in damage that will require extensive work by a qualified technician to repair.

Technical Support

International

- ♦ For online technical support – including troubleshooting, documentation, and software updates: <http://support.aten.com>
- ♦ For telephone support, see *Telephone Support*, page iv:

North America

Email Support		support@aten-usa.com
Online Technical Support	Troubleshooting Documentation Software Updates	http://www.aten-usa.com/support
Telephone Support		1-888-999-ATEN ext 4988 1-949-428-1111

When you contact us, please have the following information ready beforehand:

- ♦ Product model number, serial number, and date of purchase
- ♦ Your computer configuration, including operating system, revision level, expansion cards, and software
- ♦ Any error messages displayed at the time the error occurred
- ♦ The sequence of operations that led up to the error
- ♦ Any other information you feel may be of help

Specifications

Function		MicLIVE™ 6-CH
Audio Inputs	XLR Combo	2 x XLR-3-31 (1: GND, 2: HOT, 3: COLD) or 6.35 mm (1/4") standard TRS stereo jack female (T: HOT(L) R: COLD(R), R: GND)
	Line-in	1 x 3.5 mm (1/8") 4-pole TRRS phone female (T: HOT(L) R: COLD(R), R: GND, S: MIC. CTIA standard)
	USB Audio-in	1 x USB-C female
Audio Output	Line-out	1 x 3.5 mm (1/8") 4-pole TRRS phone female (T: HOT(L) R: COLD(R), R: GND, S: MIC. CTIA standard)
	Headphones (monitoring)	2 x 3.5 mm (1/8") TRS phone female
	USB Audio-out	1 x USB-C female
Audio Sampling		24-bit / 96 kHz
Connection		1 x USB-C female; USB bus-powered
Environmental		
Operating Temperature		0 – 40 °C
Storage Temperature		–20 – 60 °C
Humidity		0–80% RH, Non-Condensing
OS Support		◆ Mac OS 10.11 or later (64-bit only) ◆ Windows 10 or later (32/64-bit) ◆ Intel i3-series 2 GHz multicore processor (or AMD equivalent) or above ◆ 2 GB RAM (8 GB or more recommended) ◆ USB-C interface with USB 2.0 or higher compatibility
Power		
Power Consumption		DC 5 V : 2.55 W : 12 BTU
Physical Properties		
Housing		Plastic
Weight		0.42 kg (0.93 lb)
Dimensions (L x W x H)		13.05 x 18.09 x 6.27 cm (5.14 x 7.12 x 2.47 in.)

Limited Warranty

ATEN warrants its hardware in the country of purchase against flaws in materials and workmanship for a Warranty Period of two [2] years (warranty period may vary in certain regions/countries) commencing on the date of original purchase. This warranty period includes the [LCD panel of ATEN LCD KVM switches](#). Select products are warranted for an additional year (see [A+ Warranty](#) for further details). Cables and accessories are not covered by the Standard Warranty.

What is covered by the Limited Hardware Warranty

ATEN will provide a repair service, without charge, during the Warranty Period. If a product is defective, ATEN will, at its discretion, have the option to (1) repair said product with new or repaired components, or (2) replace the entire product with an identical product or with a similar product which fulfills the same function as the defective product. Replaced products assume the warranty of the original product for the remaining period or a period of 90 days, whichever is longer. When the products or components are replaced, the replacing articles shall become customer property and the replaced articles shall become the property of ATEN.

To learn more about our warranty policies, please visit our website:
<http://www.aten.com/global/en/legal/policies/warranty-policy/>