

PREZONE1

Stereo pre-amplifier/mixer with 2 stereo volume zones



The PREZONE1, a multi-functional stereo preamplifier that allows you to independently control the volume in 2 stereo zones. It gives you the possibility to mix the 2 microphone levels easily with one of the 4 music sources. The innovative and extremely intuitive design of the front panel will instantly indicate how to operate the progressive PREZONE1.

The logical rear panel will give every installer an instant understanding on how to install the unit. It's easy to distinguish the PREZONE1 from its competitors. Its higher signal to noise ratio, ease-of-use, logical design and versatile installer features makes it suitable for almost every professional audio application.

TECHNICAL SPECIFICATIONS

19" (483 mm wide) rack mounting	yes	height- rack units (1U=44 mm) in U	2
depth (build in) in mm	290	depth (incl front) in mm	305
power supply	100 - 240 VAC	power consumption (max) in watts	30
zone outputs	2 stereo	SPDIF output	no
signal to noise level SNR (dB)	>97	total harmonic distortion THD (%)	<0.2
crosstalk (dB)	>70	music level control	yes
MIC level control	yes	VCA level control	no
source selection per zone	no	MIC inputs balanced	2
inputs with Phantom power	2	Phantom power voltage in volts	48
noise gate on MIC	no	selectable input dynamics	no
selectable output dynamics	no	line input unbalanced	4
line input SPDIF	no	tone control	yes
RS232 (serial communication port)	no	priority input contact	yes
VOX mute	yes	maximum qty paging Mics	0
emergency input	yes	priority levels	3
frequency response (in Hz)	20 - 25 k	applicable in 100V	yes
applicable low impedance	yes	Net weight product (kg)	3.65

MORE PICTURES



ACCESSORIES



MICPAT-D

All call dynamic paging microphone



D-ALINP

Active local input panel Decora style



ALINP

Active local input panel