



Philips
Manual switch

2-Way
75/75/75/ ohm

SWV2007H



Ensure a reliable connection

with this 2-way manual switcher

Manually switch between two coax input sources displayed to one TV.

Enjoy good picture quality

- Crafted with quality construction

Easy installation

- Mounting screws included

Environmentally friendly

- Environmentally friendly lead-free construction

Expand your system

- A/B switch

PHILIPS

Specifications

Packaging dimensions

- Type of shelf placement: Dummy
- Packaging dimensions (W x H x D):
3,7 x 5,7 x 0,8 inch
- Nett weight: 0,095 lb
- Gross weight: 0,117 lb
- Tare weight: 0,022 lb
- UPC: 6 09585 19783 1
- Number of products included: 1
- Packaging type: Dummy

Outer Carton

- Outer carton (L x W x H): 8,9 x 7,3 x 7,5 inch

- Nett weight: 2,280 lb
- Gross weight: 4,232 lb
- Tare weight: 1,952 lb
- GTIN: 1 06 09585 19783 8
- Number of consumer packagings: 24

Inner Carton

- Inner carton (L x W x H): 7,0 x 2,2 x 4,0 inch
- Nett weight: 0,380 lb
- Gross weight: 0,661 lb
- Tare weight: 0,281 lb
- GTIN: 2 06 09585 19783 5
- Number of consumer packagings: 4

Highlights

A/B switch

Built-in selector switch makes it easy to change between viewing sources.

Lead-free construction

Lead-free construction of environmentally friendly materials.

Mounting screws included

This is all the necessary hardware you need to ideally position and secure the splitter.

Quality construction

Quality construction uses only top grade materials to create products of extended durability.



Issue date 2014-03-14

Version: 1.0.6

12 NC: 8670 000 68338
UPC: 6 09585 19783 1

© 2014 Koninklijke Philips N.V.
All Rights reserved.

Specifications are subject to change without notice.
Trademarks are the property of Koninklijke Philips N.V.
or their respective owners.

www.philips.com